## STAR 400 / 800 Emergency Power Supply



## **BATTERY NOT INCLUDED**

Capacity 400 W to be used whit 2 batteries 18 Ah

Capacity 800 W to be used whit 2 batteries 33 Ah

*Plastic box* dimensions :h 13.5x13.9x5.3 inches

| SPECIFICATIONS         | STAR 400/800 - 115V                     |
|------------------------|---|
| Using rate capacity    | 800 VA ( $\leq$ 1000W )                 |
| Transfer time          | 4 - 6 ms                                |
| Battery type           | (400VA - 18Ah x 2) - (800VA - 36Ah x 2) |
| Motor type motor scope | 400 VA ≤500W<br>800 VA ≤1000W           |
| Charging current       | 1 Amp                                   |
| Voltage range          | 85 <sup>~</sup> - 135 Vac               |

## DC Battery back up - up

- Protects the electronic unit from sudden net voltage variations (up to 187V)
- Integrated fan cooling system
- On request available with metal box and batteries
- Eliminates temporary events on the supply net thanks to active capacitive input filters
- Possibility to add external batteries KIT BAT 7 (7 Ah)
- Built in card to manage battery level for ultimate cycle
- Electronic device for assistance in case of power failure in the gate installation and allows you to open/close your door even when the power is out.



SEA USA Inc. 10850 N.W. 21st Street - Unit 160 - 33172 Miami - Florida (USA) Phone: +1-305.594.1151 - Fax: +1-305.594.7325 www.sea-usa.com