

# Wireless Intercoms System

ANSWER YOUR VIDEO INTERCOM AND OPEN YOUR GATE/DOOR FROM ANYWHERE IN THE WORLD WITH YOUR SMARTPHONE.

## **SEACOM Wi-Fi video**







Download the APP:





from Apple Store



or Google Play



- WiFi Enabled Video Intercom Use your Existing Internet
- Ideal for Vehicular & Pedestrian Gates as well as Office entrances
- Standard Gooseneck and Surface Mount Option
- Use your phone as entry credential
- Can only be set up by App (not available to program via SMS)
- Easy wireless connection to exisiting home wifi
- Get a video call from your gate/door even when you are away
- No SIM card, no call charges (data charges may apply when phone not connected to WiFi)
- No home phone line needed
- Less susceptible to lighting strikes no wire in the ground
- Simple set up by mobile phone. Connect to the system video directly through your phone's or tablet's WiFi, enter the pass code for the home hub Wi-Fi and your devices are connected.

# Specs:

- 2 relays Control up to Two Gates/Doors
- Roll Over Call feature up to 4 Phone Numbers calls all 4 devices at the same time
- Optional RJ 45 Connection for Cat 5 or Cat 6 Cable
- Long range directional patch antenna at gate (up to 30-150 yards, its depend on router and environmental condiditions)







Waterproof Mylar 1.5W speaker

Rugged watherproof, vandal and watherproof Stainless Steel Design

### **Measurements**







#### General

24Vdc voltage

Recommended cable @25 feet of 14 gauge Solar operable with high capacity panels

Current on stand-by: 90mA Operating current: 330mA Peak demand current: 2 Amps

#### Camera

Color

100° viewing angle

Mono night vision with IR illumination

640x480 pixels

## **Antenna**

2.4 Ghz frequency

14 dB gain

Range of approximately 20 yards (further from router than a phone!)

Cable: 30 feet RG58, 50 ohm, with SMA male

60° transmission angle

# Keypad module

3 relays max 2 amps 24Vac/dc load Latching 1000 codes